



KAMPANA																	
0K, 1K , 2K , KAVI/KV & KARE/KR 250																	
KW.	HP	E.MOTOR	KOD	H	P	N	D	D1	D2	FLANGE TYPE	B	B1	E	E1	L	K	M
2,2 / 4	3 / 5,5	110/112	0K250	115	250	180	25,5	215	15	TYPE 1	52,5	72	85	100	25,7	26,25	-
			1K250				TYPE 2			71.4	96.1	90	114	31,5	36	M6	
			2K250				TYPE 3			98,5	128	119	151	43	48	M8	
			3K250	-						-	137	182	-	-	-		
			KV2501	125			TYPE 5			-	-	104	132	-	-	-	
			KV2502							-	-	104	132	-	-	-	
			KV2503							-	-	147	200	-	-	-	
			KV2504	130						-	-	147	200	-	-	-	
			KR2501	115			TYPE 4			-	-	121	-	-	-	-	
			KR2502							-	-	121	-	-	-	-	
			KR2503							-	-	121	-	-	-	-	
			KR2504							-	-	121	-	-	-	-	