



KAMPANA																	
1K , 2K , 3K , KAVI/KV & KARE/KR 300																	
KW.	HP	E.MOTOR	KOD	H	P	N	D	D1	D2	FLANGE TYPE	B	B1	E	E1	L	K	M
5,5 / 10	7,5 / 10	132	1K300	135	300	230	36,5	265	15	TYPE 2	71,4	96,1	90	114	31,5	36	M6
			2K300				50,5			TYPE 3	98,5	128	119	151	43	48	M8
			3K300	144			-			-	137	182	-	-	-		
			KV3001	158			-			-	105	133	-	-	-		
			KV3002				-			-	105	133	-	-	-		
			KV3003				-			-	121	174	-	-	-		
			KV3004				-			-	121	174	-	-	-		
			KV3005				-			-	147	210	-	-	-		
			KR3001	135			-			-	121	-	-	-	-		
			KR3002				-			-	121	-	-	-	-		
			KR3003				-			-	121	-	-	-	-		
			KR3004				-			-	121	-	-	-	-		